



APLIKACJA SMART LIFE

AC520-02

SMART KONTROLER TUYA WIFI

STEROWNIK RADIOWY DO PRZESŁON OKIENNYCH.
UMOŻLIWIA STEROWANIE ZA POMOCĄ URZĄDZEŃ
MOBILNYCH DZIĘKI ŁĄCZNOŚCI Z SIECIĄ WiFi




PIERWSZE URUCHOMIENIE

1. POBIERAMY APLIKACJĘ „SMART LIFE” ZE SKLEPU PLAY/APP STORE
2. TWORZYMY NOWE KONTO W APLIKACJI
3. PODŁĄCZAMY KABEL MICRO USB DO ZASILANIA (DC 5V/1A)
MRUGAJĄCA NA NIEBIESKO DIODA LED SYGNALIZUJE GOTOWOŚĆ DO PAROWANIA
4. W „SMART LIFE” WYBIERAMY „+” LUB „DODAJ URZĄDZENIE”




POŁĄCZENIE Z AC520-02

5. URZĄDZENIE POWINNO ZOSTAĆ AUTOMATYCZNIE WYKRYTE I WYŚWIETLIĆ SIĘ NA PIERWSZYM MIEJSCU URZĄDZEŃ
6. KLIKAMY „ADD”
(JEŻELI URZĄDZENIE NIE ZOSTAŁO WYKRYTE AUTOMATYCZNIE WYSZUKUJEMY Z LISTY „SMART IR”)




KONFIGURACJA AC520-02

7. ŁĄCZYMY URZĄDZENIE Z NASZĄ SIECIĄ WIFI
8. CZEKAMY AŻ PROCES PAROWANIA ZOSTANIE ZAKOŃCZONY CO ZOSTANIE POTWIERDZONE SYMBOLEM



ŁĄCZENIE Z SILNIKIEM

9. Z LISTY POŁĄCZONYCH URZĄDZEŃ WYBIERAMY POŁĄCZONY PRZED CHWILĄ KOTROLER.
10. KLIKAMY ZIELONY PRZYCISK „ADD” I WYBIERAMY RODZAJ PRZESŁONY
11. WPROWADZAMY SILNIK W TRYB PAROWANIA (3 SEKUNDY TRZYMAJĄC PRZYCISK PROGRAMOWANIA)
12. W CIĄGU 5 SEKUND KLIKAMY „MATCH RIGHT AWAY”



13. JEŚLI POŁĄCZENIE ZOSTAŁO NAWIĄZANE. SILNIK POWINIEN ODPOWIEDZIEĆ MRUGNIĘCIEM NA NIEBIESKO LUB PORUSZENIEM SIĘ.

OBSŁUGA SILNIKA

14. JEŚLI SILNIK ZAREAGOWAŁ KLIKAMY „RESPONDING, SAVE THE REMOTE CONTROL”
15. GOTOWE
STEROWANIE ODBYWA SIĘ ZA POMOCĄ ODPOWIEDNIH PRZYCISKÓW KIERUNKOWYCH W APLIKACJI.



Częstotliwość radiowa	433.92Mhz
Moc transmisji	≤10mW
Zasilanie	DC 5V/1A
Długość [mm]	70
Szerokość [mm]	70
Wysokość [mm]	27
Temperatura pracy	-10°C÷55°C
Łączność z siecią internet	WiFi

ABY ZRESETOWAĆ URZĄDZENIE PRZYTRZYMAJ PRZYCISK „RESET”
PRZEZ 10 SEKUND



SMART LIFE APP


AC520-02 TUYA WIFI SMART CONTROLLER RADIO CONTROLLER FOR WINDOW BLINDS. TO CONTROL BY MOBILE DEVICES WiFi CONNECTED



FIRST STEPS


1. DOWNLOAD THE „SMART LIFE” APP FROM THE PLAY STORE/APP STORE
2. CREATE A NEW ACCOUNT IN THE APP
3. CONNECT THE MICRO USB CABLE TO POWER (DC 5V / 1A)
4. IN „SMART LIFE” SELECT „+” OR „ADD DEVICE”

BLUE BLINKING LED INDICATES DEVICE IS READY FOR PAIRING




CONNECTION WITH AC520-02

5. THE DEVICE SHOULD BE AUTOMATICALLY DETECTED AND DISPLAY ON THE FIRST PLACE OF DEVICES
6. CLICK „ADD”
(IF THE DEVICE WAS NOT DETECTED AUTOMATICALLY WE SEARCH FROM THE „SMART IR” LIST)




AC520-02 CONFIGURATION

7. CONNECT THE DEVICE TO WIFI NETWORK
8. WAIT UNTIL THE PAIRING PROCESS WILL BE COMPLETED WHAT WILL BE CONFIRMED BY THE  SYMBOL



CONNECTING TO THE MOTOR

9. CHOOSE FROM THE LIST OF CONNECTED DEVICES CONNECTED A AC520-02 CONTROLLER.
10. CLICK THE GREEN „ADD” BUTTON AND CHOOSE THE TYPE OF THE BLIND (3 SECONDS HOLDING THE MOTOR PROGRAMMING BUTTON)
11. PUT THE MOTOR INTO THE **PAIRING MODE**
12. WITHIN 5 SECONDS, CLICK „MATCH RIGHT AWAY”



13. WHEN THE CONNECTION WAS ESTABLISHED. THE MOTOR SHOULD RESPOND WITH A BLINK OF BLUE OR MOVE.

MOTOR CONTROL

14. IF THE MOTOR RESPONDED, CLICK „RESPONDING, SAVE THE REMOTE CONTROL”
15. **READY**

CONTROL BY THE APPROPRIATE DIRECTION BUTTONS IN THE APP.



Radio frequency	433.92Mhz
Transmission power	≤10mW
Power	DC 5V/1A
Length [mm]	70
Width [mm]	70
Height [mm]	27
Working temperature	-10°C÷55°C
Internet connectivity	WiFi

TO RESET THE DEVICE HOLD THE RESET BUTTON FOR 10 SECONDS